

DRT-9600



Features

- ⇒ Front end circuit embedded
- ⇒ Volume controller for variable output
- ⇒ Can adjust the step by UP/DOWN buttons and remember 30 frequencies for each FM and AM
- ⇒ Mute circuit embedded to remove the noise for clear listening
- ⇒ Able to choose the output mode as mono or stereo

Specification

	DRT-9600
Output	600mV / 600Ω
Frequency Response (±3dB)	FM : 80Hz ~ 12KHz / AM : 125Hz ~ 1.8KHz
T.H.D	FM : ≤0.2% / AM : ≤1%
S/N	FM : ≥60dB / AM : ≥50dB
Tuning Range	FM : 87.5MHz ~ 108MHz / AM : 552KHz ~ 1611KHz
Frequency Step	70Hz ~ 9KHz
Sensitivity	FM : 10dB / AM : 30dB
Auto Stop	FM : 29dB / AM : 20dB
Power Source	AC 220V / 60Hz / DC 24V
Power Consumption	5.5W (MAX)
Weight	1.2kg
Dimension (W × H × D)	482 × 44 × 280