

MP-9600



Features

- ⇒ Can check level meter by LED lights
- ⇒ Can select among 8 power amplifiers and monitor selected amplifier's output sound by embedded speaker
- ⇒ Switches for adjusting volume of monitoring speaker (0dB / -6dB / -12dB / -18dB / -24dB)

Specification

	MP-9600
Monitor Output	3W (MAX)
Sensitivity	High Voltage (70V or 100V)
Monitoring Speaker Control	0dB / -6dB / -12dB / -18dB / -24dB
Power Consumption	200mV
Input Channel	8CH
Power Source	DC 24V
Weight	4.3kg
Dimension (W × H × D)	482 × 88 × 280